

Some new additivity results on quantum channels

Motohisa Fukuda
Statistical Laboratory
Centre for Mathematical Science
University of Cambridge
Wilberforce Road,
Cambridge CB3 0WB UK

16 May 2005

Abstract

In this paper we introduce a lemma. This lemma states that for a unitary covariant channel and a channel M such that $M(\rho_0)$ is of rank one for some state $\rho_0 \in S(H)$ the additivity of the minimal output entropy of M implies that of M , and the multiplicativity of the maximal output p -norm of M , that of M . For the product channel of the depolarising channel and an arbitrary channel the additivity of the minimal output entropy, the multiplicativity of the maximal output p -norm for $p \in [0, 1]$ and the additivity of the Holevo capacity are established [1], [2]. Applying the lemma to these results we produce a new class of memoryless quantum channels for which the additivity of the minimal output entropy and the multiplicativity of the maximal output p -norm hold. This class of channels are defined as a linear combination of a channel M satisfying the above property and the completely noisy channel: $N(\rho) = M(\rho) + (1 - \alpha) \frac{1}{d} I$, where $\alpha \in [\frac{1}{d^2 - 1}, 1]$, d is the dimension of the signal Hilbert space H and I is the identity operator. A similar property was used in a recent paper [3]. An interesting example of this class is the shifted depolarising channel, for which the multiplicativity is shown for $p = 2$ in [4], [5]. The additivity of the Holevo capacity for the above class of channels is also proved under an additional condition that M is irreducibly covariant.

Email: m.fukuda@statslab.cam.ac.uk

1 Introduction

1.1 Basic definitions and facts

A quantum state (a state) is represented as a positive semidefinite operator of trace one in a Hilbert space H of dimension d ; this is called a density operator. The set of density operators in H is written as $S(H)$. A (memoryless) channel on H is a completely positive trace-preserving (CPTP) map acting on the algebra of operators in H .

Definition 1

1) The minimal output entropy (M O E) of Φ is defined as

$$S_{\min}(\Phi) := \inf_{\rho \in S(H)} S(\Phi(\rho)); \quad (1.1)$$

where S is the von Neumann entropy: $S(\rho) = -\text{tr}[\rho \log \rho]$.

2) The maximal output p-norm of Φ is defined as

$$\|\Phi\|_p := \sup_{\rho \in S(H)} \|\Phi(\rho)\|_p; \quad (1.2)$$

where $\|\cdot\|_p$ is the (trace) p-norm: $\|\rho\|_p = (\text{tr} |\rho|^p)^{\frac{1}{p}}$. Note that

$$\frac{d}{dp} \|\rho\|_p = S(\rho); \quad \frac{d}{dp} \|\Phi\|_p = S_{\min}(\Phi); \quad (1.3)$$

3) The Holevo capacity of Φ is defined as

$$C(\Phi) := \sup_{\{p_i, \rho_i\}} S\left(\sum_i p_i \Phi(\rho_i)\right) - \sum_i p_i S(\rho_i); \quad (1.4)$$

where $\{p_i, \rho_i\}$ stands for a (finite) ensemble of states (p_i is a probability distribution and $\rho_i \in S(H)$).

The Holevo capacity admits the following representation (the OPW-SW representation) [6],[7]:

$$C(\Phi) = \inf_{\rho \in S(H)} \sup_{\sigma \in S(H)} S(\Phi(\rho) \parallel \sigma); \quad (1.5)$$

where $S(\rho||\sigma) = \text{tr}[(\log \rho - \log \sigma)\rho] = S(\rho) - \text{tr}[\log \sigma \rho]$ is the relative entropy of two states ρ and σ .

Definition 2

1) A channel Φ is unitary covariant if for any unitary operator U there exists a unitary operator V such that

$$(\Phi(U \rho U^*)) = V (\Phi(\rho)) V^* ;$$

for $\rho \in \mathcal{S}(\mathcal{H})$.

2) Take a compact group G and a continuous unitary representation V_g of G in \mathcal{H} . A channel Φ is covariant with respect to the representation if

$$(\Phi(V_g \rho V_g^*)) = V_g (\Phi(\rho)) V_g^*$$

for $g \in G$ and $\rho \in \mathcal{S}(\mathcal{H})$.

3) A channel Φ is irreducibly covariant if Φ is covariant with respect to an irreducible representation.

Remark. Suppose a channel Φ is irreducibly covariant then Φ is unital and we have the formula [8],[9]:

$$S(\Phi(\rho)) = \log d - S_{\min}(\rho); \quad (1.6)$$

1.2 Conjectures and our results

The following three conjectures attracted attention in recent years.

1) The additivity conjecture of the M O E is that for channels Φ and Ψ

$$S_{\min}(\Phi \otimes \Psi) = S_{\min}(\Phi) + S_{\min}(\Psi); \quad (1.7)$$

Note that the bound $S_{\min}(\Phi \otimes \Psi) \leq S_{\min}(\Phi) + S_{\min}(\Psi)$ is straightforward.

2) The multiplicativity conjecture of the maximal output p-norm is that for channels Φ and Ψ there exists $p > 0$ such that

$$\Phi_p(\Phi \otimes \Psi) = \Phi_p(\Phi) \Phi_p(\Psi); \quad (1.8)$$

for any $p \in [1; 1 + \frac{1}{d}]$. Note that the bound $p(\Phi \otimes \Psi) \leq p(\Phi) + p(\Psi)$ is straightforward.

The multiplicativity conjecture is connected with that of additivity of the M O E. If multiplicativity holds then taking the derivative at $p = 1$ we get additivity of the M O E.

3) The additivity conjecture of the Holevo capacity is that for channels Φ and Ψ

$$C(\Phi \otimes \Psi) = C(\Phi) + C(\Psi): \quad (1.9)$$

Note that the bound $C(\Phi \otimes \Psi) \leq C(\Phi) + C(\Psi)$ is straightforward. In particular if we prove

$$C(\Phi^{\otimes n}) = n C(\Phi)$$

for $n \geq 2, N$, then we can identify the classical information capacity $C(\Phi)$:

$$C(\Phi) := \lim_{n \rightarrow \infty} \frac{1}{n} C(\Phi^{\otimes n}) = C(\Phi):$$

For irreducibly covariant channels, the additivity of the M O E and the additivity of the Holevo capacity are equivalent.

The variety of channels for which either of the above properties have been proved is rather limited and includes unital qubit channels [10], entanglement-breaking channels [11], depolarising channels [1][2], Werner-Holevo channels [12],[13],[14] and their modifications [3],[15],[16].

In section 2 we introduce a lemma. This lemma states that for a unitary covariant channel Φ and a channel M such that $M(\rho_0)$ is of rank one for some state $\rho_0 \in S(H)$ the additivity of the M O E of Φ implies that of $\Phi \otimes M$, and the multiplicativity of the maximal output p-norm of Φ , that of $\Phi \otimes M$.

In section 3 we produce new classes of channels for which either the additivity of the M O E or the multiplicativity of the maximal output p-norm holds. One of these classes is very interesting because it includes the shifted depolarising channel. This class of channels are defined as a linear combination of a channel M having the above property and a completely noisy channel:

$$\Phi(\rho) = M(\rho) + (1 - \frac{1}{d}) \frac{1}{d} I: \quad (1.10)$$

Here $\frac{1}{d^2} \in [\frac{1}{d^2-1}; 1]$, d is the dimension of the signal Hilbert space H and I is the identity operator. This class of channels is introduced by [3]. Our result is that for the product channel of a channel Φ from this class and an arbitrary channel Ψ we establish the additivity of the M O E and the multiplicativity of the maximal output p-norm for $p \in [1; 1 + \frac{1}{d}]$.

In section 4 we mention the additivity of the Holevo capacity for the above class of channels under an additional condition that M is irreducibly covariant.

2 The Lemma

Lemma. Suppose we have two channels on H : a unitary covariant channel \mathcal{U} and a channel M such that $M(\rho_0)$ is of rank one for some state $\rho_0 \in S(H)$. Take another Hilbert space K and a channel \mathcal{V} on K .

- 1) If the maximal output p -norm of \mathcal{U} is multiplicative then so is that of $(\mathcal{U} \otimes M)$ (for the same p).
- 2) If the M O E of \mathcal{U} is additive then so is that of $(\mathcal{U} \otimes M)$.

Proof. First calculate the maximal output p -norm of M .

$$\begin{aligned} p(\mathcal{U} \otimes M) &= \sup_{\rho \in S(H \otimes K)} k(\mathcal{U} \otimes M(\rho)) k_p \\ &= \sup_{M \in S(H)} k(\mathcal{U}(M)) k_p \\ &= p(\mathcal{U}): \end{aligned}$$

Note that since channel \mathcal{U} is unitary covariant the maximal output p -norm of \mathcal{U} is attained at any state of rank one. On the other hand, $M(S(H))$, the image of M , has such a state $M(\rho_0)$ for some $\rho_0 \in S(H)$. This verifies the above equality.

Next, take any state $\rho \in S(H \otimes K)$ then

$$\begin{aligned} k((\mathcal{U} \otimes M)(\rho)) k_p &= k(\mathcal{U}(\mathcal{U}^{-1}(\rho)) (M \otimes 1_K)(\rho)) k_p \\ &= p(\mathcal{U}) p(M) \\ &= p(\mathcal{U} \otimes M) p(\rho): \end{aligned}$$

Therefore we have

$$p((\mathcal{U} \otimes M)(\rho)) = p(\mathcal{U} \otimes M) p(\rho):$$

Similarly, for any state $\rho \in S(H \otimes K)$

$$S(((\mathcal{U} \otimes M)(\rho))^{(\wedge)}) = S_{\min}(\rho) + S_{\min}(\rho) = S_{\min}(\mathcal{U} \otimes M(\rho)) + S_{\min}(\rho):$$

Hence we have

$$S_{\min}((\mathcal{U} \otimes M)(\rho)) = S_{\min}(\mathcal{U} \otimes M(\rho)) + S_{\min}(\rho):$$

Lemma has been proved.

Remark. The conditions on \mathcal{U} and M are not necessary if we verify that a maximiser of $k(\rho) k_p$ (or a minimiser of $S(\rho)$) coincides an output of M .

3 Applications

We apply Lemma in section 2 to the known results and produce new classes of channels for which either the additivity of the M O E or the multiplicativity of the maximal output p-norm holds.

Example 1. The depolarising channel is defined by

$$\Phi(\rho) = \frac{1}{d} \text{Tr}(\rho) I + (1 - \frac{1}{d}) \rho \quad (3.1)$$

Here $\frac{1}{d} \in [0, 1]$, d is the dimension of the signal Hilbert space H and I is the identity operator. The additivity of the M O E and the multiplicativity of the maximal output p-norm for $p \in [0, 1]$ are established for the product channel of the depolarising channel and an arbitrary channel [1, 2].

Take a channel M having the property in Lemma and define a class of channels in the form :

$$\Phi(\rho) = M(\rho) + (1 - \frac{1}{d}) \rho \quad (3.2)$$

where $\frac{1}{d} \in [0, 1]$. Since the depolarising channel is unitary covariant the additivity of the M O E and the multiplicativity of the maximal output p-norm for $p \in [0, 1]$ hold for the product channel of a channel from this class and an arbitrary channel.

The shifted depolarising channel is defined by

$$\Phi(\rho) = a \rho + b \text{Tr}(\rho) |j\rangle\langle j| + \frac{1}{d} \rho \quad (3.3)$$

Here $|j\rangle\langle j|$ is a fixed state of rank one and $a + b + \frac{1}{d} = 1$. The multiplicativity of the maximal output p-norm for $p = 2$ was proved for the shifted depolarising channel [4, 5]. To see that this channel belongs to the above class define a channel M by

$$M(\rho) = \frac{a}{a+b} \rho + \frac{b}{a+b} |j\rangle\langle j| \text{Tr}(\rho)$$

and set

$$a = a + b$$

Note that M has an output of rank one: $M(|j\rangle\langle i|) = |j\rangle\langle i|$. So we have established the additivity of the M O E and the multiplicativity of the maximal output p-norm for $p \in [1; 1]$ for the product channel of the shifted depolarising channel and an arbitrary channel.

Example 2. The transpose depolarising channel is defined by

$$\Phi(\rho) = \rho^T + (1 - \frac{1}{d})\frac{1}{d}I; \quad (3.4)$$

Here $\frac{1}{d} \in [0; 1]$, T is the transpose, d is the dimension of the signal Hilbert space H and I is the identity operator. The additivity of the M O E for the product channel of these two channels is proved [15],[16]. Take a channel M having the above property again and define:

$$\Phi(\rho) = M(\rho)^T + (1 - \frac{1}{d})\frac{1}{d}I; \quad (3.5)$$

for $\frac{1}{d} \in [0; 1]$. Since the transpose depolarising channel is unitary covariant the additivity of the M O E holds.

Remark. A class of channels which satisfy the hypotheses in Lemma have been studied by N. Datta and M. B. Ruskai who independently established additivity for this class [17].

4 Additivity of the Holevo capacity

In section 3 we produced the class of channels defined in the form (3.2):

$$\Phi(\rho) = M(\rho) + (1 - \frac{1}{d^2})\frac{1}{d}I;$$

Here $\frac{1}{d^2} \in [0; 1]$ and channel M has the property in Lemma. We claim that if M is irreducibly covariant (hence so is Φ) as well the additivity of the Holevo capacity holds for the product channel of a channel from this class and an arbitrary channel. It can be proved by extending the method by C. King [1].

First, the phase-damping channel can be written by

$$\Phi(\rho) = \rho + \sum_{i=1}^{X^d} (1 - p_i) E_i \rho E_i^\dagger \quad (4.1)$$

Here $\sum_{i=1}^{X^d} p_i = 1$ and $E_i = |v_i\rangle\langle v_i|$ for some orthonormal basis $\{|v_i\rangle\}_{i=1}^{X^d}$ in H . We say Φ is uniform in basis B if the co-ordinate representations of $|v_i\rangle$ in basis B are

$$|v_i\rangle = \begin{pmatrix} v_{i1} \\ v_{i2} \\ \vdots \\ v_{id} \end{pmatrix} \quad \text{where } |v_{ij}|^2 = \frac{1}{d} \text{ for } 1 \leq i \leq X^d, 1 \leq j \leq d$$

We extend Lemma 8 in [1] by using this definition. For a fixed basis B the channel can be written as a convex combination of triple compositions:

$$\Phi = \sum_{k=1}^N c_k U_k^{(k)} M \quad (4.2)$$

Here $N \leq X^d$, coefficients $c_k > 0$, $\sum_{k=1}^N c_k = 1$, U_k are unitary matrices, $U_k^\dagger U_k = I$ and $U_k^{(k)}$ are phase-damping channels which are uniform in basis B .

Next, $\rho \in S(H \otimes K)$ and let $\rho = (M \otimes I)^N \rho_0$. For any $\rho \in S(H \otimes K)$ the derivative at $p=1$ of the inequality (34) in [1] gives

$$\begin{aligned} & S(\rho) - S(\rho_0) \\ &= S(\rho) - \log d + \sum_{i=1}^{X^d} \text{tr}[\rho^{(i)}] \log \text{tr}[\rho^{(i)}] - \sum_{i=1}^{X^d} \text{tr}[\rho_0^{(i)}] S(\rho_0^{(i)}) \\ &= S(\rho) - \log d - \frac{1}{d} \sum_{i=1}^{X^d} S(\rho_0^{(i)}): \end{aligned} \quad (4.3)$$

Here $\rho_0^{(i)} = \text{tr}_1[(E_i \otimes I) \rho_0]$. Note that as $\text{tr}_2[\rho]$ admits a diagonal matrix representation with respect to its eigenbasis B , we could have chosen each $\rho \in S(H \otimes K)$ to be uniform in the basis B . Hence we get

$$\text{tr}[\rho_0^{(i)}] = \text{tr}_2[\text{tr}_1[(E_i \otimes I) \rho]] = \text{tr}_1[E_i \text{tr}_2[\rho]] = \frac{1}{d}$$

Suppose \mathcal{U} achieves the minimum in the OPW SW representation (1.5) of \mathcal{H} . We calculate

$$\begin{aligned} S(\rho(\mathcal{M})) &= S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) \\ &= S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) \\ &= S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) \\ &= S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) + \log d \sum_{i=1}^d \frac{1}{d} \rho_i \log \left(\frac{1}{d}\right) : \end{aligned} \quad (4.4)$$

Note that each ρ_i is a state and $\sum_{i=1}^d \rho_i = \rho$.

Combining (4.3) and (4.4)

$$S(\rho(\mathcal{M})) \geq S(\rho) + \log d \sum_{i=1}^d \frac{1}{d} \rho_i \log \left(\frac{1}{d}\right)$$

This inequality holds for $\mathcal{H}(\mathcal{K})$ and $\mathcal{H}(\mathcal{K}) \leq \mathcal{H}(\mathcal{K})$.

Finally since the von Neumann entropy is concave and ρ has output $\frac{1}{d} \rho$ (because is irreducibly covariant) we have

$$\begin{aligned} S(\rho) &\geq S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) \\ &\geq S\left(\sum_{i=1}^d \frac{1}{d} \rho_i\right) \\ &\geq S(\rho) + \log d \sum_{i=1}^d \frac{1}{d} \rho_i \log \left(\frac{1}{d}\right) : \end{aligned}$$

Note that the decomposition $\rho = \sum_{k=1}^N p_k \rho_k$ depends on \mathcal{U} . The claim has been verified.

5 Conclusion

The decomposition $\rho = \sum_{k=1}^N p_k \rho_k$ in Lemma is interesting. We can put nice structures into ρ_k and the rest M to decompose some channels. From another perspective, for a fixed

unitary covariant channel \mathcal{F} , $\mathcal{F} \subseteq \mathcal{M}_{G_M}$ form a subset of quantum channels. Then we only have to verify the additivity of the M O E (or the multiplicativity of the maximal output p-norm) for \mathcal{F} to prove the additivity (or the multiplicativity) for all channels in the subset. I hope the lemma produce other classes of channels for which either the additivity or the multiplicativity holds.

Acknowledgement. I would like to thank my supervisor Yuri Suhov for suggesting the problem, constant encouragement and numerous discussions. Nilanjana Datta is thanked for her attention and numerous discussions. Mary-Beth Ruskai helped me with some important remarks. I would like to thank Mary-Beth Ruskai, Christopher King and Denes Petz for giving me important remarks on the initial version of the paper and correcting references in it.

References

- [1] C. King, "The capacity of the quantum depolarizing channel", *IEEE Trans. Inform. Theory*, 49, 221{229, (2003).
- [2] A. Fujiwara and T. Hashizume, "Additivity of the capacity of depolarizing channels", *Phys. Lett. A*, 299, 469{475 (2002).
- [3] M. M. Wolf and J. Eisert, "Classical information capacity of a class of quantum channels", *New J. Phys.*, 7, 93 (2005).
- [4] V. Giovannetti, S. Lloyd and M. B. Ruskai, "Conditions for multiplicativity of maximal p-norms of channels for fixed integer p", *J. Math. Phys.*, 46, 042105 (2005).
- [5] C. King, M. Nathanson and M. B. Ruskai, "Multiplicativity properties of entrywise positive maps", *quant-ph/0409181*.
- [6] M. Ohya, D. Petz and N. Watanabe, "On capacities of quantum channels", *Prob. Math. Stat.*, 17 179{196 (1997).
- [7] B. Schumacher and M. D. Westmoreland, "Relative entropy in quantum information theory", *quant-ph/0004045*.
- [8] A. S. Holevo, "Remarks on the classical capacity of quantum channel", *quant-ph/0212025*.

- [9] J. Cortese, "The Holevo-Schumacher-Westmoreland channel capacity for a class of qudit unital channels", quant-ph/0211093.
- [10] C. King, "Additivity for unital qubit channels", J. Math. Phys. 43, 4641{4653, (2002).
- [11] P. W. Shor, "Additivity of the classical capacity of entanglement-breaking quantum channels", J. Math. Phys. 43, 4334{4340, (2002).
- [12] K. Matsumoto and F. Yura, "Entanglement cost of antisymmetric states and additivity of capacity of some quantum channels", J. Phys. A, 37, L167{L171 (2004).
- [13] N. Datta, A. S. Holevo and Y. Suhov, "A quantum channel with additive minimum output entropy", quant-ph/0403072.
- [14] R. Alicki and M. Fannes, "Note on multiple additivity of minimal Renyi entropy output of the Werner-Holevo channels", quant-ph/0407033.
- [15] N. Datta, A. S. Holevo and Y. Suhov, "Additivity for transpose depolarizing channels", quant-ph/0412034.
- [16] M. Fannes, B. Haegeman, M. Mosonyi and D. Vanpeteghem, "Additivity of minimal entropy output for a class of covariant channels", quant-ph/0410195.
- [17] N. Datta and M. B. Ruskai, "Maximal output purity and capacity for asymmetric unital qudit channels", quant-ph/0505048.