LIMIT THEOREMS FOR FREE MULTIPLICATIVE CONVOLUTIONS

HARI BERCOVICI AND JIUN-CHAU WANG

ABSTRACT. We determine the distributional behavior for products of free random variables in a general infinitesimal triangular array. The main theorems in this paper extend a result for measures supported on the positive half-line in [4], and provide a new limit theorem for measures on the unit circle with nonzero first moment.

1. INTRODUCTION

Given two probability measures μ , ν on $\mathbb{R}_+ = (0, +\infty)$, we will denote by $\mu \otimes \nu$ their classical multiplicative convolution, and by $\mu \boxtimes \nu$ their free multiplicative convolution. Thus, $\mu \otimes \nu$ is the distribution of XY, where X and Y are classically independent positive random variables with distributions μ and ν , respectively. Analogously, $\mu \boxtimes \nu$ is the distribution of $X^{1/2}YX^{1/2}$, where X and Y are freely independent positive random variables with distributions μ and ν . A triangular array $\{\nu_{nk} : n \geq 1, 1 \leq k \leq k_n\}$ of probability measures on \mathbb{R}_+ is said to be *infinitesimal* if

$$\lim_{n \to \infty} \max_{1 \le k \le k_n} \nu_{nk}(\{t \in \mathbb{R}_+ : |t - 1| \ge \varepsilon\}) = 0,$$

for every $\varepsilon > 0$. Given such an array, one is interested in the asymptotic behavior of the measures

$$\mu_n = \nu_{n1} \circledast \nu_{n2} \circledast \cdots \circledast \nu_{nk_r}$$

and

$$\nu_n = \nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n}.$$

The case of μ_n is completely understood, and is reduced to the theory of addition of independent random variables by a logarithmic change of variables. However, the free case ν_n does not simply reduce to the additive theory by this change of variables.

The problem was first addressed in [4], where a triangular array such that $\nu_{n1} = \nu_{n2} = \cdots = \nu_{nk_n}$ for all *n* was considered. In this case, necessary and sufficient conditions were found for the weak convergence of the measures ν_n . In particular, it was shown that the sequence ν_n converges weakly if μ_n converges, but not conversely.

In this paper we will find necessary and sufficient conditions for the weak convergence of ν_n without any further assumptions on the infinitesimal array. We also prove analogous results for infinitesimal triangular arrays on the unit circle $\mathbb{T} = \{z \in \mathbb{C} : |z| = 1\}$. In both cases the possible limit of ν_n is \boxtimes -infinitely divisible as shown in [8, 2].

The additive version of our results were studied earlier. Thus, consider an array $\{\mu_{nk}: n \ge 1, 1 \le k \le k_n\}$ of probability measures on \mathbb{R} . Infinitesimality in this case means that

$$\lim_{n \to \infty} \max_{1 \le k \le k_n} \mu_{nk}(\{t \in \mathbb{R} : |t| \ge \varepsilon\}) = 0, \qquad \varepsilon > 0.$$

Denote by

$$\lambda_n = \mu_{n1} * \mu_{n2} * \dots * \mu_{nk_n}$$

the classical additive convolutions, and by

$$\rho_n = \mu_{n1} \boxplus \mu_{n2} \boxplus \cdots \boxplus \mu_{nk_n}$$

the free additive convolutions of these measures. When $\mu_{n1} = \mu_{n2} = \cdots = \mu_{nk_n}$ for all *n*, it was shown in [3] that λ_n converges weakly if and only if ρ_n converges weakly. This result was extended to arbitrary infinitesimal arrays by Chistyakov and Götze in [9]. These authors made heavy use of analytic subordination (first proved for the free additive convolution in [11] generically and in [7] for the general case; cf. also [12, 13], [1] and [8] for different approaches). Our methods do not require analytic subordination and are close to the original approach in [4].

The remainder of this paper is organized as follows. In Section 2, we describe the analytical apparatus necessary for the calculation of free multiplicative convolutions. We also describe the \boxtimes -infinitely divisible measures on \mathbb{R}_+ and \mathbb{T} and some useful approximation results. In Sections 3 we give the convergence criteria for arrays on \mathbb{R}_+ , and in Section 4, we prove the analogous result for \mathbb{T} .

2. Preliminaries

The analogue of Fourier transform for multiplicative free convolutions was discovered by Voiculescu [10] (see also [5, 6]). Denote by \mathcal{M}_+ the collection of Borel probability measures defined on \mathbb{R}_+ , and by $\mathcal{M}_{\mathbb{T}}^{\times}$ Borel probability measures ν supported on the circle \mathbb{T} with nonzero first moment, i.e. $\int_{\mathbb{T}} t \, d\nu(t) \neq 0$.

Given $\nu \in \mathcal{M}_+$, one defines the analytic function ψ_{ν} by

$$\psi_{\nu}(z) = \int_0^\infty \frac{tz}{1 - tz} \, d\nu(t), \qquad z \in \mathbb{C} \setminus (0, +\infty).$$

The function ψ_{ν} is univalent in the left half-plane $i\mathbb{C}^+$, and $\psi_{\nu}(i\mathbb{C}^+)$ is a region contained in the circle with diameter (-1,0); moreover, $\psi_{\nu}(i\mathbb{C}^+) \cap (-\infty,0) = (-1,0)$. Setting $\Omega_{\nu} = \psi_{\nu}(i\mathbb{C}^+)$, one defines the *S*-transform of the measure ν to be

$$S_{\nu}(z) = \frac{1+z}{z} \psi_{\nu}^{-1}(z), \qquad z \in \Omega_{\nu}.$$

The remarkable property of the S-transform is that for $\mu, \nu \in \mathcal{M}_+$, one has

$$S_{\mu\boxtimes\nu}(z) = S_{\mu}(z)S_{\nu}(z),$$

for every z in a neighborhood of (-1, 0).

For $\nu \in \mathcal{M}_{\mathbb{T}}^{\times}$, the function ψ_{ν} is defined by the formula given above (with the integral calculated over \mathbb{T}), but its domain of definition is now the open unit disk $\mathbb{D} = \{z \in \mathbb{C} : |z| < 1\}$. The function ψ_{ν} has an inverse in a neighborhood of zero since $\psi'_{\nu}(0) = \int_{\mathbb{T}} t \, d\nu(t) \neq 0$. The corresponding S-transform is defined in a neighborhood of zero. It is sometimes convenient to use a variation of the S-transform:

$$\Sigma_{\nu}(z) = S_{\nu}\left(\frac{z}{1-z}\right).$$

If $\nu \in \mathcal{M}_{\mathbb{T}}^{\times}$, the function Σ_{ν} is also defined in a neighborhood of zero, and

$$\Sigma_{\mu\boxtimes\nu}(z) = \Sigma_{\mu}(z)\Sigma_{\nu}(z), \qquad \mu, \nu \in \mathcal{M}_{\mathbb{T}}^{\times},$$

for all z in a neighborhood of zero where all functions involved are defined.

The weak convergence of probability measures can be translated in terms of their S-transforms.

Theorem 2.1. [5, 6]

- Given {ν_n}[∞]_{n=1} ⊂ M₊, the sequence {ν_n}[∞]_{n=1} converges weakly to a measure ν ∈ M₊ if and only if there exist two positive numbers 0 < b < a < 1 such that the disk D with the diameter (-a, -b) is contained in Ω_{ν_n} for all n, and the sequence {S_{ν_n}}[∞]_{n=1} converges uniformly on D to a function S.
- (2) Given $\{\nu_n\}_{n=1}^{\infty} \subset \mathcal{M}_{\mathbb{T}}^{\times}$, the sequence $\{\nu_n\}_{n=1}^{\infty}$ converges weakly to a measure $\nu \in \mathcal{M}_{\mathbb{T}}^{\times}$ if and only if there exists a neighborhood of zero $K \subset \mathbb{D}$ such that for all Σ_{ν_n} are defined in K, and the sequence $\{\Sigma_{\nu_n}\}_{n=1}^{\infty}$ converges uniformly on K to a function Σ .

Moreover, if (1) is satisfied then $S = S_{\nu}$, and if (2) is satisfied then $\Sigma = \Sigma_{\nu}$.

An array $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_{\mathbb{T}}^{\times}$ is infinitesimal if

$$\lim_{n \to \infty} \max_{1 \le k \le k_n} \nu_{nk} (\{t \in \mathbb{T} : |\arg t| \ge \varepsilon\}) = 0,$$

for every $\varepsilon > 0$; here the principal value of the argument is used. The following proposition gives an approximation of the S-transform (see Theorem 3.1 in [4] and Theorem 1.1 and Theorem 2.1 in [2]).

Proposition 2.2. For 0 < b < a < 1 and $\varepsilon \in (0, 1)$, define \overline{D} to be the closed disk with diameter [-a, -b], and set $K_{\varepsilon} = \{z \in \mathbb{C} : |z| \leq \varepsilon\}$.

(1) If an array $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_+$ is infinitesimal, then the functions $S_{\nu_{nk}}$ are defined in \overline{D} for sufficiently large n, and we have

$$S_{\nu_{nk}}(z) = 1 + \left[\int_0^\infty \frac{1-t}{1+z-tz} \, d\nu_{nk}(t)\right] (1+u_{nk}(z)),$$

for all $z \in \overline{D}$, where $\lim_{n \to \infty} \max_{1 \le k \le k_n} |u_{nk}(z)| = 0$ uniformly on \overline{D} .

(2) If an array $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_{\mathbb{T}}^{\times}$ is infinitesimal, then $S_{\nu_{nk}}$ are defined in K_{ε} when n is large, and we have

$$S_{\nu_{nk}}(z) = 1 + \left[\int_{\mathbb{T}} \frac{1-t}{1+z-tz} \, d\nu_{nk}(t) \right] (1+v_{nk}(z)),$$

for all $z \in K_{\varepsilon}$, where $\lim_{n \to \infty} \max_{1 \le k \le k_n} |v_{nk}(z)| = 0$ uniformly on K_{ϵ} .

A measure $\nu \in \mathcal{M}_+$ is said to be \circledast -infinitely divisible if, for each $n \in \mathbb{N}$, there exists a measure $\nu_n \in \mathcal{M}_+$ such that

$$\nu = \underbrace{\nu_n \circledast \nu_n \circledast \cdots \circledast \nu_n}_{n \text{ times}}.$$

The notion of \boxtimes -infinite divisibility is defined analogously. The study of \circledast -infinitely divisible measures on \mathbb{R}_+ reduces (by a change of variable) to the study of the usual \ast -infinitely divisible measures on \mathbb{R} . The Fourier transform needs to be replaced by the Mellin-Fourier transform of a measure $\nu \in \mathcal{M}_+$ defined by

$$\Phi_{\nu}(s) = \int_0^\infty t^{is} \, d\nu(t), \qquad s \in \mathbb{R}.$$

The fundamental property of the Mellin-Fourier transform is that

$$\Phi_{\mu \circledast \nu}(s) = \Phi_{\mu}(s)\Phi_{\nu}(s).$$

A \circledast -infinitely divisible measure $\nu \in \mathcal{M}_+$ has the Mellin-Fourier transform

$$\Phi_{\nu}(s) = \exp\left[i\lambda s + \int_0^\infty \left(t^{-is} - 1 + \frac{is\log t}{\log^2 t + 1}\right) \frac{\log^2 t + 1}{\log^2 t} d\rho(t)\right], \qquad s \in \mathbb{R},$$

where $\lambda \in \mathbb{R}$ and ρ is a finite positive Borel measure on \mathbb{R}_+ . We use the notation $\nu_{\circledast}^{\lambda,\rho}$ to denote the \circledast -infinitely divisible measure determined by λ and ρ . For \boxtimes -infinite divisibility we have the following formulas as in [5, 6]. A measure $\nu \in \mathcal{M}_+$ is \boxtimes infinitely divisible if and only if there exist $\gamma \in \mathbb{R}$ and a finite positive Borel measure σ on the compact space $[0, +\infty]$ such that $S_{\nu}(z) = \exp(v_{\gamma,\sigma}(z))$, where $v_{\gamma,\sigma}$ is given by

$$v_{\gamma,\sigma}\left(\frac{z}{1-z}\right) = \gamma - \sigma(\{+\infty\})z + \int_{[0,+\infty)}\frac{1+tz}{z-t}\,d\sigma(t), \qquad z \in \mathbb{C} \setminus [0,1].$$

A measure $\nu \in \mathcal{M}_{\mathbb{T}}^{\times}$ is \boxtimes -infinitely divisible if and only if there exist $\gamma \in \mathbb{R}$ and a finite positive Borel measure σ on \mathbb{T} such that $\Sigma_{\nu}(z) = \exp(u_{\gamma,\sigma}(z))$, where $u_{\gamma,\sigma}$ is

given by

$$u_{\gamma,\sigma}(z) = -i\gamma + \int_{\mathbb{T}} \frac{1+tz}{1-tz} d\sigma(t), \qquad z \in \mathbb{D}.$$

We denote by $\nu_{\boxtimes}^{\gamma,\sigma}$ the \boxtimes -infinitely divisible measure determined by γ and σ . There is a unique \boxtimes -infinitely divisible measure m on \mathbb{T} such that its first moment is zero. This is the Haar, or normalized arclength measure.

We conclude this section with a result which will be used repeatedly.

Lemma 2.3. Consider a sequence $\{r_n\}_{n=1}^{\infty} \subset \mathbb{R}$ and two triangular arrays $\{z_{nk} : n \geq 1, 1 \leq k \leq k_n\}$, $\{w_{nk} : n \geq 1, 1 \leq k \leq k_n\}$ of complex numbers. Assume that

- (1) $\Im w_{nk} \ge 0$, for $n \ge 1$ and $1 \le k \le k_n$.
- (2)

$$z_{nk} = w_{nk}(1 + \varepsilon_{nk}),$$

where

$$\varepsilon_n = \max_{1 \le k \le k_n} |\varepsilon_{nk}|$$

converges to zero as $n \to \infty$.

(3) There exists a positive constant M such that for sufficiently large n,

$$|\Re w_{nk}| \le M \Im w_{nk}.$$

Then the sequence $\{r_n + \sum_{k=1}^{k_n} z_{nk}\}_{n=1}^{\infty}$ converges if and only if the sequence $\{r_n + \sum_{k=1}^{k_n} w_{nk}\}_{n=1}^{\infty}$ converges. Moreover, the two sequences have the same limit.

Proof. The assumptions on $\{z_{nk}\}_{n,k}$ and $\{w_{nk}\}_{n,k}$ imply

(2.1)
$$\left| \left(r_n + \sum_{k=1}^{k_n} z_{nk} \right) - \left(r_n + \sum_{k=1}^{k_n} w_{nk} \right) \right| \le 2(1+M)\varepsilon_n \left(\sum_{k=1}^{k_n} \Im w_{nk} \right),$$

and

(2.2)
$$(1 - \varepsilon_n - M\varepsilon_n) \left(\sum_{k=1}^{k_n} \Im w_{nk} \right) \le \left| \sum_{k=1}^{k_n} \Im z_{nk} \right|,$$

for sufficiently large *n*. If the sequence $\{r_n + \sum_{k=1}^{k_n} z_{nk}\}_{n=1}^{\infty}$ converges to a complex number *z*, (2.2) implies that $\{\sum_{k=1}^{k_n} \Im w_{nk}\}_{n=1}^{\infty}$ is bounded, and then (2.1) shows that the sequence $\{r_n + \sum_{k=1}^{k_n} w_{nk}\}_{n=1}^{\infty}$ also converges to *z*. Conversely, if $\{r_n + \sum_{k=1}^{k_n} w_{nk}\}_{n=1}^{\infty}$ converges to *z*, then the sequence $\{\sum_{k=1}^{k_n} \Im w_{nk}\}_{n=1}^{\infty}$ is bounded and hence by (2.1) the sequence $\{r_n + \sum_{k=1}^{k_n} w_{nk}\}_{n=1}^{\infty}$ converges to *z* as well.

3. Free Multiplicative Convolution on \mathbb{R}_+

Given an infinitesimal triangular array $\{\nu_{nk} : 1 \leq k \leq k_n, n \in \mathbb{N}\} \subset \mathcal{M}_+$ and $\tau > 0$, define positive numbers

$$b_{nk} = \exp\left(\int_{e^{-\tau}}^{e^{\tau}} \log t \, d\nu_{nk}(t)\right),$$

and measures ν_{nk}° by

$$d\nu_{nk}^{\circ}(t) = d\nu_{nk}(b_{nk}t).$$

Obviously, $\max_{1 \le k \le k_n} |b_{nk} - 1| \to 0$ as $n \to \infty$, and hence the array $\{\nu_{nk}^\circ\}_{n,k}$ is also infinitesimal. Define

$$g_{nk}(w) = \int_0^\infty \frac{t^2 - 1}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) + \int_0^\infty \left[\frac{1 + tw}{w - t}\right] \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right),$$

for $w \in \mathbb{C} \setminus [0, +\infty)$. Note that $g_{nk}(\overline{w}) = \overline{g_{nk}(w)}$ and $\Im g_{nk}(w) \leq 0$ for all w such that $\Im w > 0$.

Lemma 3.1. For every compact set $K \subset \mathbb{C}^+ \cap (i\mathbb{C}^+)$ there exists a positive constant $M = M(\tau, K)$ such that for sufficiently large n, we have

$$|\Re g_{nk}(w)| \le M |\Im g_{nk}(w)|, \qquad w \in K, \ 1 \le k \le k_n.$$

Proof. We assume for convenience that $\tau = 1$. No generality is lost since one can make a linear change of variable to modify the value of τ . By a change of variable we have

$$\int_0^\infty \frac{t^2 - 1}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) = \int_{-\infty}^\infty \frac{1 - e^{2x}}{1 + e^{2x}} \, d\rho_{nk}(x + a_{nk})$$

and

$$\int_0^\infty \frac{(t-1)^2}{t^2+1} \, d\nu_{nk}^\circ\left(\frac{1}{t}\right) = \int_{-\infty}^\infty \frac{(1-e^x)^2}{1+e^{2x}} \, d\rho_{nk}(x+a_{nk}),$$

where the probability measure ρ_{nk} is defined as $d\rho_{nk}(x) = d\nu_{nk}(e^x)$, and $a_{nk} = \int_{|x|<1} x \, d\rho_{nk}(x)$. Note that the family $\{\rho_{nk}\}_{n,k}$ is now an infinitesimal family of probability measures on \mathbb{R} , and hence

$$\lim_{n \to \infty} \max_{1 \le k \le k_n} |a_{nk}| = 0.$$

We proceed by rewriting

$$\int_{-\infty}^{\infty} \frac{1 - e^{2x}}{1 + e^{2x}} d\rho_{nk}(x + a_{nk}) = \int_{|x| < 1} \left[\frac{1 - e^{2(x - a_{nk})}}{1 + e^{2(x - a_{nk})}} + (x - a_{nk}) \right] d\rho_{nk}(x) - \int_{|x| \ge 1} a_{nk} d\rho_{nk}(x) + \int_{|x| \ge 1} \frac{1 - e^{2(x - a_{nk})}}{1 + e^{2(x - a_{nk})}} d\rho_{nk}(x).$$

It is easy to see that

$$\left|1 - e^{2(x - a_{nk})} + (x - a_{nk}) + (x - a_{nk})e^{2(x - a_{nk})}\right| \le 60(x - a_{nk})^2,$$

for |x| < 1. Consequently, for all n and k we have

$$\left| \int_{|x|<1} \left[\frac{1 - e^{2(x - a_{nk})}}{1 + e^{2(x - a_{nk})}} + (x - a_{nk}) \right] d\rho_{nk}(x) \right| \le 60 \int_{-\infty}^{\infty} \frac{(1 - e^x)^2}{1 + e^{2x}} d\rho_{nk}(x + a_{nk}).$$

Since the family $\{\rho_{nk}\}_{n,k}$ is infinitesimal, there exists $N \in \mathbb{N}$ such that

$$|a_{nk}| \le \frac{1}{2}$$

for all $n \geq N$, $1 \leq k \leq k_n$. Note that

$$\frac{(1-e^x)^2}{1+e^{2x}} \ge \frac{(1-\sqrt{e})^2}{1+e} \quad \text{and} \quad 5(1-e^x)^2 \ge \left|1-e^{2x}\right|,$$

for all $|x| \ge \frac{1}{2}$. We deduce that for $n \ge N$, $1 \le k \le k_n$ we have

$$\left| \int_{|x|\ge 1} a_{nk} \, d\rho_{nk}(x) \right| \le \int_{|x|\ge 1} d\rho_{nk}(x)$$
$$\le \frac{1+e}{(1-\sqrt{e})^2} \int_{-\infty}^{\infty} \frac{(1-e^x)^2}{1+e^{2x}} \, d\rho_{nk}(x+a_{nk}),$$

and

$$\left| \int_{|x|\ge 1} \frac{1-e^{2(x-a_{nk})}}{1+e^{2(x-a_{nk})}} \, d\rho_{nk}(x) \right| \le 5 \int_{-\infty}^{\infty} \frac{(1-e^x)^2}{1+e^{2x}} \, d\rho_{nk}(x+a_{nk}).$$

Therefore, for sufficiently large n,

$$\left| \int_0^\infty \frac{t^2 - 1}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t} \right) \right| \le 74 \int_0^\infty \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t} \right).$$

The compactness of the set K implies the existence of positive constants M_1 and M_2 such that

$$\left| \Re \left[\frac{1+tw}{w-t} \right] \right| \le M_1$$

and

$$\Im\left[\frac{1+tw}{w-t}\right] = -\Im\left[\frac{1+tw}{w-t}\right] \ge M_2,$$

for all $t \in (0, +\infty)$ and $w \in K$. Hence, we have for sufficiently large n and for $w \in K$,

$$\begin{aligned} |\Re g_{nk}(w)| &= \left| \int_0^\infty \frac{t^2 - 1}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) + \int_0^\infty \Re \left[\frac{1 + tw}{w - t}\right] \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) \right| \\ &\leq 74 \int_0^\infty \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) + M_1 \int_0^\infty \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) \\ &\leq \frac{(74 + M_1)}{M_2} \int_0^\infty M_2 \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) \\ &\leq -\frac{(74 + M_1)}{M_2} \int_0^\infty \Im \left[\frac{1 + tw}{w - t}\right] \frac{(t - 1)^2}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) \\ &= \frac{74 + M_1}{M_2} \left|\Im g_{nk}(w)\right|. \end{aligned}$$

The result follows with $M = (74 + M_1)/M_2$.

Fix a closed disk $\overline{D} \subset i\mathbb{C}^+$ with diameter [-a, -b], where 0 < b < a < 1. By Proposition 2.2, $S_{\nu_{nk}}$ is defined in \overline{D} for large n. Setting w = z/(1+z), and using the identity

$$\frac{(w-1)(t-1)}{w-t} = \frac{t^2-1}{t^2+1} + \left[\frac{1+tw}{w-t}\right]\frac{(t-1)^2}{t^2+1},$$

we see that the function $S_{\nu_{nk}^{\circ}}$ admits the following approximation:

$$S_{\nu_{nk}^{\circ}}\left(\frac{w}{1-w}\right) - 1 = g_{nk}(w)\left(1 + u_{nk}\left(\frac{w}{1-w}\right)\right),$$

in another closed disk $\overline{D_0} = \{z/(1+z): z \in \overline{D}\}$ with real center, and

$$\lim_{n \to \infty} \max_{1 \le k \le k_n} \left| u_{nk} \left(\frac{w}{1 - w} \right) \right| = 0,$$

uniformly for all $w \in \overline{D_0}$. Note that

$$S_{\nu_{nk}^{\circ}}\left(\frac{w}{1-w}\right) = b_{nk}S_{\nu_{nk}}\left(\frac{w}{1-w}\right)$$

The infinitesimality of the array $\{\nu_{nk}\}_{n,k}$ also shows that $S_{\nu_{nk}}(z)$ converges uniformly in k and $z \in \overline{D}$ to 1 as $n \to \infty$; indeed, $S_{\delta_1} \equiv 1$. Hence, for sufficiently large n, the principal branch of $\log S_{\nu_{nk}}(z)$ is defined in \overline{D} . Furthermore, since

$$\log w = w - 1 + o(|w - 1|),$$

as $w \to 1$, it is easy to see from Lemma 3.1 and Lemma 2.3 that we have the following result. Fix a real number γ , and a finite positive Borel measure σ on $[0, +\infty]$.

Lemma 3.2. Let $\{\alpha_n\}_{n=1}^{\infty}$ be a sequence of positive real numbers. Then the sequence of functions $\{-\log \alpha_n + \sum_{k=1}^{k_n} \log S_{\nu_{nk}}(z)\}_{n=1}^{\infty}$ converges to $\nu_{\gamma,\sigma}(z)$ uniformly for all $z \in \overline{D}$ as $n \to \infty$ if and only if

$$\lim_{n \to \infty} \left(-\log \alpha_n + \sum_{k=1}^{k_n} \left[g_{nk}(w) - \log b_{nk} \right] \right) = v_{\gamma,\sigma} \left(\frac{w}{1 - w} \right)$$

uniformly for all $w \in \overline{D_0}$.

Theorem 3.3. For an infinitesimal family $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_+$ and a sequence $\{\alpha_n\}_{n=1}^{\infty} \subset \mathbb{R}_+$, the following two assertions are equivalent:

- (1) The sequence $\nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\alpha_n}$ converges weakly to $\nu_{\boxtimes}^{\gamma,\sigma}$.
- (2) The sequence of measures

$$d\sigma_n(t) = \sum_{k=1}^{k_n} \frac{(t-1)^2}{t^2+1} \, d\nu_{nk}^{\circ}\left(\frac{1}{t}\right)$$

converges weakly in $[0, +\infty]$ to σ , and the sequence

$$\gamma_n = -\log \alpha_n + \sum_{k=1}^{k_n} \left[\int_0^\infty \frac{t^2 - 1}{t^2 + 1} \, d\nu_{nk}^\circ \left(\frac{1}{t}\right) - \log b_{nk} \right]$$

converges to γ as $n \to \infty$.

Proof. Assume (1) holds. From Theorem 2.1, there exists a closed disk \overline{D} with real center such that

$$\lim_{n \to \infty} \left(\frac{1}{\alpha_n} \prod_{k=1}^{k_n} S_{\nu_{nk}}(z) \right) = S_{\nu_{\boxtimes}^{\gamma,\sigma}}(z) = \exp(v_{\gamma,\sigma}(z))$$

uniformly on the disk \overline{D} . We may choose \overline{D} small enough so that $\exp(v_{\gamma,\sigma}(z))$ is in $-i\mathbb{C}^+$ on \overline{D} . Applying the principal branch of the logarithm function, we deduce that

$$\lim_{n \to \infty} \left(-\log \alpha_n + \sum_{k=1}^{k_n} \log S_{\nu_{nk}}(z) \right) = v_{\gamma,\sigma}(z),$$

uniformly on \overline{D} . Thus, Lemma 3.2 implies that

(3.1)
$$\lim_{n \to \infty} \left(-\log \alpha_n + \sum_{k=1}^{k_n} \left[g_{nk}(w) - \log b_{nk} \right] \right) = v_{\gamma,\sigma} \left(\frac{w}{1-w} \right)$$

uniformly on $\overline{D_0} = \{ z/(1+z) : z \in \overline{D} \}$. Note that

(3.2)
$$-\log \alpha_n + \sum_{k=1}^{k_n} \left[g_{nk}(w) - \log b_{nk} \right] = \gamma_n + \int_0^\infty \frac{1+tw}{w-t} \, d\sigma_n(t).$$

Considering the imaginary part of the equation (3.1), we have

(3.3)
$$-\Im w \int_{[0,+\infty)} \frac{1+t^2}{|w-t|^2} d\sigma(t) = -\lim_{n \to \infty} \Im w \int_{(0,+\infty)} \frac{1+t^2}{|w-t|^2} d\sigma_n(t).$$

Note that the function $t \mapsto \frac{1+t^2}{|w-t|^2}$ is bounded away from zero and infinity for all $w \in \overline{D_0}$; moreover, if $\Im w \neq 0$ then (3.3) shows that

$$\sup_n \sigma_n((0,+\infty)) < +\infty,$$

and hence the family $\{\sigma_n\}_{n=1}^{\infty}$ has a weak cluster point σ' on the compact space $[0, +\infty]$. Then (3.3) shows that $\sigma' = \sigma$, and consequently the measures σ_n converges weakly to σ on $[0, +\infty]$ as $n \to \infty$. Then it is easy to see from (3.1) and (3.2) that $\lim_{n\to\infty} \gamma_n = \gamma$.

Conversely, assume (2) holds. The infinitesimality of the array $\{\nu_{nk}\}_{n,k}$ implies that there exist $a', b' \in (0, 1)$ with b' < a' such that $S_{\nu_{nk}}$ are defined in $\overline{D'}$, the closed disk with the diameter [-a', -b'], for sufficiently large n. Let $\overline{D'_0} = \{z/(1+z) : z \in \overline{D'}\}$ and observe that there exists a positive constant M = M(a', b') such that

$$\left|\frac{1+tw}{w-t}\right| \le M, \qquad w \in \overline{D'_0}, \ t \in (0, +\infty).$$

Thus, in view of (3.2), we deduce that (3.1) holds pointwise in $\overline{D'_0}$. Since $\Im g_{nk}(w) \leq 0$ for $w \in D'_0 \cap i\mathbb{C}^+$, the family $\{-\log \alpha_n + \sum_{k=1}^{k_n} [g_{nk}(w) - \log b_{nk}]\}_{n=1}^{\infty}$ is normal in

 $D_0' \cap i\mathbb{C}^+$. Moreover, note that $g_{nk}(\overline{w}) = \overline{g_{nk}(w)}$ and

$$v_{\gamma,\sigma}\left(\frac{\overline{w}}{1-\overline{w}}\right) = \overline{v_{\gamma,\sigma}\left(\frac{w}{1-w}\right)},$$

for $w \in \overline{D'_0}$. Therefore, as an application of Montel's theorem, we conclude that (3.1) holds uniformly on compact subsets of $\overline{D'_0}$. From Lemma 3.2 we conclude that there exists a smaller closed disk $\overline{D''} \subset \overline{D'}$ with real center, such that

$$\lim_{n \to \infty} \left(-\log \alpha_n + \sum_{k=1}^{k_n} \log S_{\nu_{nk}}(z) \right) = v_{\gamma,\sigma}(z),$$

uniformly on $\overline{D''}$. Applying the exponential, we obtain

$$\lim_{n \to \infty} \left(\frac{1}{\alpha_n} \prod_{k=1}^{k_n} S_{\nu_{nk}}(z) \right) = S_{\nu_{\boxtimes}^{\gamma,\sigma}}(z) = \exp(v_{\gamma,\sigma}(z))$$

uniformly on $\overline{D''}$. Therefore (1) follows from Theorem 2.1.

It has been pointed out in [4] that the weak convergence criteria for products of free and independent random variables are not equivalent. Nevertheless, the following correspondence is true.

Corollary 3.4. Given an infinitesimal family $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_+$ and a sequence $\{\alpha_n\}_{n=1}^{\infty} \subset \mathbb{R}_+$, the following two statements are equivalent:

- (1) The sequence $\nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\alpha_n}$ converges weakly to $\nu_{\boxtimes}^{\gamma,\sigma}$ and $\sigma(\{0\}) = \sigma(\{\infty\}) = 0;$
- (2) The sequence $\nu_{n1} \circledast \nu_{n2} \circledast \cdots \circledast \nu_{nk_n} \circledast \delta_{\alpha_n}$ converges weakly to $\nu_{\circledast}^{\lambda,\rho}$.

If conditions (1) and (2) are satisfied then the measure σ and ρ are related by

$$d\sigma(t) = \frac{\log^2 t + 1}{\log^2 t} \frac{(t-1)^2}{t^2 + 1} d\rho(t)$$

and

$$\gamma - \lambda = \int_0^\infty \left(\frac{t^2 - 1}{t^2 + 1} + \frac{\log^2 t}{\log^2 t + 1} \right) \frac{\log^2 t + 1}{\log^2 t} \, d\rho(t).$$

Proof. The proof is identical with that of Theorem 4.2 in [4].

4. Free Multiplicative Convolution on $\mathbb T$

Fix an infinitesimal array $\{\nu_{nk} : n \geq 1, 1 \leq k \leq k_n\} \subset \mathcal{M}_{\mathbb{T}}^{\times}$ and $\tau \in (0, \pi)$. Consider the centering constant

$$b_{nk} = \exp\left(\int_{|\arg t| < \tau} \log t \, d\nu_{nk}(t)\right),$$

and the centered measure ν_{nk}° obtained as follows:

$$d\nu_{nk}^{\circ}(t) = \frac{d\nu_{nk}(b_{nk}t)}{10}.$$

Here, as before, $\log t = i \arg t$ represents the principal branch of $\log t$. We have $\max_{1 \le k \le k_n} |\arg b_{nk}| \to 0$ as $n \to \infty$, and hence the array $\{\nu_{nk}^\circ\}_{n,k}$ is also infinitesimal. Define

$$h_{nk}(z) = -i \int_{\mathbb{T}} \Im t \, d\nu_{nk}^{\circ}(t) + \int_{\mathbb{T}} \frac{1+tz}{1-tz} (1-\Re t) \, d\nu_{nk}^{\circ}(t), \qquad z \in \mathbb{D}.$$

Note that $\Re h_{nk}(z) \ge 0$ for all $z \in \mathbb{D}$.

Lemma 4.1. For every compact neighborhood of zero $K \subset \mathbb{D}$, there exists a positive constant $M = M(\tau, K)$ such that for sufficiently large n, we have

$$|\Im h_{nk}(z)| \le M \Re h_{nk}(z), \qquad z \in K, \ 1 \le k \le k_n.$$

Proof. We may again assume that $\tau = 1$. Define probability measures ρ_{nk} on \mathbb{R} such that $\rho_{nk}(\sigma) = \nu_{nk}(e^{i\sigma})$ if $\sigma \subset [-\pi, \pi)$, and $\rho_{nk}(\sigma) = 0$ when $\sigma \cap [-\pi, \pi) = \phi$. Changing variables, we have

$$\int_{\mathbb{T}} \Im t \, d\nu_{nk}^{\circ}(t) = \int_{-\infty}^{\infty} \sin x \, d\rho_{nk}(x + a_{nk})$$

and

$$\int_{\mathbb{T}} (1 - \Re t) \, d\nu_{nk}^{\circ}(t) = \int_{-\infty}^{\infty} (1 - \cos x) \, d\rho_{nk}(x + a_{nk})$$

where $a_{nk} = \int_{|x|<1} x \, d\rho_{nk}(x) = \int_{|\arg t|<1} \arg t \, d\nu_{nk}(t)$. The infinitesimality of the family $\{\nu_{nk}\}_{n,k}$ implies that for sufficiently large n,

$$\max_{1 \le k \le k_n} |a_{nk}| \le \frac{1}{10}$$

By using the elementary inequalities

$$|\sin x - x| \le 2(1 - \cos x), \qquad -2 \le x \le 2,$$

and

$$\frac{1}{10} + |\sin x| \le 10(1 - \cos x), \text{ where } \frac{9}{10} \le |x| \le \pi + \frac{9}{10},$$

we have,

$$\begin{aligned} \left| \int_{\mathbb{T}} \Im t \, d\nu_{nk}^{\circ}(t) \right| &\leq \left| \int_{|x|<1} \left[\sin(x - a_{nk}) - (x - a_{nk}) \right] \, d\rho_{nk}(x) \right| \\ &+ \left| \int_{[-\pi, -1] \cup [1, \pi)} a_{nk} \, d\rho_{nk}(x) \right| + \left| \int_{[-\pi, -1] \cup [1, \pi)} \sin(x - a_{nk}) \, d\rho_{nk}(x) \right| \\ &\leq 12 \int_{\mathbb{T}} (1 - \Re t) \, d\nu_{nk}^{\circ}(t), \end{aligned}$$

for large n and $1 \leq k \leq k_n$. Also, from the compactness of the set K, there exist two positive constants M_1 and M_2 such that

$$\left| \Re \left[\frac{1+tz}{1-tz} \right] \right| = \Re \left[\frac{1+tz}{1-tz} \right] \ge M_1$$

and

$$\left|\Im\left[\frac{1+tz}{1-tz}\right]\right| \le M_2,$$

for all $t \in \mathbb{T}$ and $z \in K$. The result follows with $M = (12 + M_2)/M_1$.

Suppose $K \subset \mathbb{D}$ is a neighborhood of zero. The infinitesimality of the array $\{\nu_{nk}\}_{n.k}$ implies that $S_{\nu_{nk}}(z)$ converges uniformly in k and $z \in K$ to 1 as $n \to \infty$, and hence for sufficiently large n, $\Sigma_{\nu_{nk}}(z)$ and the principal branch of $\log \Sigma_{\nu_{nk}}(z)$ are defined in $K' = \{z/(1+z) : z \in K\}$.

Fix a real number γ , and a finite positive Borel measure σ on \mathbb{T} .

Lemma 4.2. Let $\{\lambda_n\}_{n=1}^{\infty} \subset \mathbb{T}$. Then

$$\lim_{n \to \infty} \exp\left(-\log \lambda_n + \sum_{k=1}^{k_n} \log \Sigma_{\nu_{nk}}(z)\right) = \Sigma_{\nu_{\boxtimes}^{\gamma,\sigma}}(z)$$

uniformly on K' if, and only if

$$\lim_{n \to \infty} \exp\left(-\log \lambda_n + \sum_{k=1}^{k_n} \left[h_{nk}(z) - \log b_{nk}\right]\right) = \sum_{\nu_{\boxtimes}^{\gamma,\sigma}} (z)$$

uniformly on K'.

Proof. From Proposition 2.2, we have the following approximation for the function $S_{\nu_{nk}^{\circ}}$:

$$S_{\nu_{nk}^{\circ}}(z) = 1 + \left[\int_{\mathbb{T}} \frac{1-t}{1+z-tz} \, d\overline{\nu}_{nk}(t) \right] (1+v_{nk}(z)), \qquad z \in K,$$

where

$$v_n(z) = \max_{1 \le k \le k_n} |v_{nk}(z)|$$

satisfies $\lim_{n\to\infty} v_n(z) = 0$ uniformly in K. Introducing a change of variable $z \mapsto \frac{z}{1-z}$ and using the identity

$$\frac{(1-t)(1-z)}{1-tz} = -i\Im t + \frac{1+tz}{1-tz}(1-\Re t),$$

we conclude that

$$b_{nk} \Sigma_{\nu_{nk}}(z) = \Sigma_{\nu_{nk}^{\circ}}(z) = 1 + h_{nk}(z) \left(1 + v_{nk} \left(\frac{z}{1-z} \right) \right), \qquad z \in K'.$$

Lemmas 4.1 and 2.3 imply that for any sequence of purely imaginary numbers $\{r_n\}_{n=1}^{\infty}$, the sequence $\{r_n + \sum_{k=1}^{k_n} [\sum_{\nu_{nk}^{\circ}}(z) - 1]\}_{n=1}^{\infty}$ converges uniformly on K' if and only if the sequence $\{r_n + \sum_{k=1}^{k_n} h_{nk}(z)\}_{n=1}^{\infty}$ converges uniformly on K'. Moreover, two sequences have the same limit. Since $\log w/(w-1) \to 1$ as $w \to 1$, we can replace $\sum_{\nu_{nk}^{\circ}}(z) - 1$ by $\log \sum_{\nu_{nk}^{\circ}}(z)$. The result follows by choosing $r_n = -\log \lambda_n - \sum_{k=1}^{k_n} \log b_{nk}$.

Theorem 4.3. For an infinitesimal array $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_{\mathbb{T}}^{\times}$ and a sequence $\{\lambda_n\}_{n=1}^{\infty} \subset \mathbb{T}$, the following assertions are equivalent:

- (1) The sequence $\nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\lambda_n}$ converges weakly to $\nu_{\boxtimes}^{\gamma,\sigma}$.
- (2) The sequence of measures

$$d\sigma_n(t) = \sum_{k=1}^{k_n} (1 - \Re t) \, d\nu_{nk}^{\circ}(t)$$

converges weakly on \mathbb{T} to σ , and the limit

$$\lim_{n \to \infty} e^{i\gamma_n} = e^{i\gamma}$$

exists, where

$$\gamma_n = \arg \lambda_n + \sum_{k=1}^{k_n} \left[\int_{\mathbb{T}} \Im t \, d\nu_{nk}^{\circ}(t) + \arg b_{nk} \right].$$

Proof. Assume (1) holds. From Theorem 2.1, there exists $\varepsilon \in (0,1)$ such that all $\Sigma_{\nu_{nk}}$ are defined in $K'_{\varepsilon} = \{z/(1+z) : |z| \le \varepsilon\}$, and we have

$$\lim_{n \to \infty} \left(\frac{1}{\lambda_n} \prod_{k=1}^{k_n} \Sigma_{\nu_{nk}}(z) \right) = \Sigma_{\nu_{\boxtimes}^{\gamma,\sigma}}(z) = e^{u_{\gamma,\sigma}(z)}$$

uniformly on K'_{ε} . Hence, by Lemma 4.2 and the definition of $u_{\gamma,\sigma}(z)$, we have (4.1)

$$\lim_{n \to \infty} \exp\left(-\log \lambda_n + \sum_{k=1}^{k_n} \left[h_{nk}(z) - \log b_{nk}\right]\right) = \exp\left(-i\gamma + \int_{\mathbb{T}} \left[\frac{1+tz}{1-tz}\right] \, d\sigma(t)\right)$$

uniformly on K'_{ε} . Taking the absolute value on both sides of (4.1), we deduce that

(4.2)
$$\lim_{n \to \infty} \exp\left(\Re\left[\sum_{k=1}^{k_n} h_{nk}(z)\right]\right) = \exp\left(\int_{\mathbb{T}} \Re\left[\frac{1+tz}{1-tz}\right] \, d\sigma(t)\right)$$

uniformly on K'_{ε} . Note that

(4.3)
$$-\log \lambda_n + \sum_{k=1}^{k_n} \left[h_{nk}(z) - \log b_{nk} \right] = -i\gamma_n + \int_{\mathbb{T}} \left[\frac{1+tz}{1-tz} \right] \, d\sigma_n(t).$$

Moreover, the real part of the function $-\log \lambda_n + \sum_{k=1}^{k_n} [h_{nk}(z) - \log b_{nk}]$ is the Poisson integral of the measure $d\sigma_n\left(\frac{1}{t}\right)$ and hence (4.2) uniquely determines the weak cluster point of $\{\sigma_n\}_{n=1}^{\infty}$ which is σ . We therefore conclude the weak convergence of the sequence $\{\sigma_n\}_{n=1}^{\infty}$. Moreover, consider z = 0 in (4.1) and (4.2) to deduce that

$$\lim_{n \to \infty} \frac{e^{i\gamma}}{e^{i\gamma_n}} = 1,$$

as desired.

The converse implication is fairly easy now, since one can basically reverse the steps to reach the statement (1) by using Lemma 4.2 and the fact that $\{-\log \lambda_n + \sum_{k=1}^{k_n} [h_{nk}(z) - \log b_{nk}]\}_{n=1}^{\infty}$ is normal in \mathbb{D} . Therefore the details of the proof are left to the reader.

The previous result does not cover the possibility that the measures $\nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\lambda_n}$ might converge to Haar measure m. We address now this special case. Let us also note for further use the equality

$$\Sigma_{\nu}(0) = \frac{1}{\int_{\mathbb{T}} t \, d\nu(t)}, \qquad \nu \in \mathcal{M}_{\mathbb{T}}^{\times}$$

Theorem 4.4. For an infinitesimal array $\{\nu_{nk}\}_{n,k} \subset \mathcal{M}_{\mathbb{T}}^{\times}$ and a sequence $\{\lambda_n\}_{n=1}^{\infty} \subset \mathbb{T}$, the following assertions are equivalent:

(1) The sequence $\nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\lambda_n}$ converges weakly to m.

(2)

$$\lim_{n \to \infty} \sum_{k=1}^{k_n} \int_{\mathbb{T}} (1 - \Re t) \, d\nu_{nk}^{\circ}(t) = +\infty.$$

Proof. Assume (2) holds. Define

$$\nu_n = \nu_{n1} \boxtimes \nu_{n2} \boxtimes \cdots \boxtimes \nu_{nk_n} \boxtimes \delta_{\lambda_n}, \qquad n \in \mathbb{N}$$

The compactness of \mathbb{T} implies that $\{\nu_n\}_{n=1}^{\infty}$ is tight. Suppose ν is a weak cluster point of $\{\nu_n\}_{n=1}^{\infty}$. From the free multiplicative analogue of Hinčin's theorem (Theorem 2.1 in [2]), the measure ν is \boxtimes -infinitely divisible. By passing to a subsequence, we may assume that ν_n converges weakly to ν as $n \to \infty$. By (4.3), we can reformulate the statement (2) as follows:

$$\lim_{n \to \infty} \Re \sum_{k=1}^{k_n} h_{nk}(0) = +\infty.$$

Then the inequality (2.2) implies that

$$\lim_{n \to \infty} \Re \sum_{k=1}^{k_n} \log \Sigma_{\nu_{nk}}(0) = +\infty,$$

and consequently we deduce that

$$\begin{aligned} \left| \int_{\mathbb{T}} t \, d\nu(t) \right| &= \lim_{n \to \infty} \left| \int_{\mathbb{T}} t \, d\nu_n(t) \right| \\ &= \lim_{n \to \infty} \frac{1}{\left| \prod_{k=1}^{k_n} \Sigma_{\nu_{nk}}(0) \right|} \\ &= \lim_{n \to \infty} \exp\left(-\Re \sum_{k=1}^{k_n} \log \Sigma_{\nu_{nk}}(0) \right) = 0. \end{aligned}$$

Therefore, the \boxtimes -infinitely divisible measure ν has zero first moment, and hence we conclude that $\nu = m$. Moreover, the full sequence ν_n converges weakly to m since $\{\nu_n\}_{n=1}^{\infty}$ has a unique weak cluster point m.

Conversely, assume (1) holds but (2) fails to be true. By passing, if necessary, to a subsequence, we may assume the sequence of measures

$$d\sigma_n(t) = \sum_{k=1}^{k_n} (1 - \Re t) \, d\nu_{nk}^{\circ}(t)$$

converges weakly to a finite positive Borel measure σ on \mathbb{T} . Since the sequence of functions $\{-\log \lambda_n + \sum_{k=1}^{k_n} [h_{nk}(z) - \log b_{nk}]\}_{n=1}^{\infty}$ is normal in \mathbb{D} , we may assume, by passing to a further subsequence, that

$$\lim_{n \to \infty} \left(-\log \lambda_n + \sum_{k=1}^{k_n} \left[h_{nk}(z) - \log b_{nk} \right] \right) = f(z),$$

uniformly on compact subsets of \mathbb{D} , where the function f is analytic in \mathbb{D} . Note that the function f is not identically infinity since

$$\Re f(z) = \lim_{n \to \infty} \int_{\mathbb{T}} \Re \left[\frac{1+tz}{1-tz} \right] \, d\sigma_n(t) = \int_{\mathbb{T}} \Re \left[\frac{1+tz}{1-tz} \right] \, d\sigma(t), \qquad z \in \mathbb{D}.$$

Then, as in the proof of Theorem 4.3, we conclude that there exists $\gamma \in \mathbb{R}$ such that

$$\lim_{n \to \infty} e^{i\gamma_n} = e^{i\gamma},$$

where the number γ_n is defined as in Theorem 4.3. An application of Theorem 4.3 then shows that a subsequence of $\{\nu_n\}_{n=1}^{\infty}$ converges weakly to $\nu_{\boxtimes}^{\gamma,\sigma}$ which contradicts (1). Therefore (2) must be true.

References

- S. T. Belinschi and H. Bercovici, Atoms and regularity for measures in a partially defined free convolution semigroup, Math. Z. 248 (2004), no. 4, 665-674.
- [2] —, *Hinčin's theorem for multiplicative free convolution*, Canadian Math. Bulletin, to appear.
- [3] H. Bercovici and V. Pata, Stable laws and domain of attraction in free probability, with an appendix by Ph. Biane, Ann. Math. 149 (1999), 1023-1060.
- [4] , Limit laws for products of free and independent random variables, Studia Math. 141 (2000), no. 1, 43-52.
- H. Bercovici and D. V. Voiculescu, Lévy-Hinčin type theorems for multiplicative and additive free convolution, Pacific J. Math. 153 (1992), no. 2, 217-248.
- [6] —, Free convolution of measures with unbounded support, Indiana Univ. Math. J. 42 (1993), no. 3, 733-773.
- [7] Ph. Biane, Processes with free increments, Math. Z. 227 (1995), no. 1, 143-174.
- [8] G. P. Chistyakov and F. Götze, The arithmetic of distributions in free probability, Arxiv: math. PS/0508245.
- [9] ——, Limit theorems in free probability. I, Arxiv: math. PS/0602219.

- [10] D. V. Voiculescu, Multiplication of certain noncommuting random variables, J. Operator Theory 18 (1987), 223-235.
- [11] —, The analogues of entropy and of Fisher's information measure in free probability. I, Comm. Math. Phys. 155 (1993), no. 1, 71-92.
- [12] —, The coalgebra of the free difference quotient and free probability, Int. Math. Res. Not.
 2000 (2000), no. 2, 79-106.
- [13] —, Analytic subordination consequence of free Markovianity, Indiana Univ. Math. J. 51 (2002), no. 5, 1161-1166.